


Ingesola

- Hybrid Inverter -



TBB Ingesola 10T/12T/15T series are three-phase hybrid inverters for residential hybrid ESS, to cut electricity cost and reliance on the grid. Suitable for low voltage battery(48V) systems, it features a 1.95 max DC/AC ratio and 3 MPPT trackers for efficient solar integration. It handles three-phase unbalanced outputs, and supports both off-grid and grid-tie operations.

It offers a smart port for configurations like secondary AC output, AC Coupling for retrofitting, generator input for backup power, and EV charging with EV and V2G chargers. Ideal for optimizing self-consumption, the Ingesola series also includes an EMS for peak shaving with eight configurable time periods for charging and discharging, and has an IP65-rated design for durability in harsh environments.

Enhanced Flexibility

- Supports both off-grid and grid-tie operations
- For Hybrid ESS, AC Coupling Retrofitting, Backup Power and EV Charging applications
- Two AC inputs or two AC outputs
- Smart port for GEN input, AC Coupling with PV inverter, EV charging, or 2nd AC output

Superior Reliability

- Three-phase unbalanced output
- Max. charging/discharging current of 300A
- Dust-and water-proof IP65 rated enclosure

ESS Capabilities

- Maximize self-consumption
- Lower electricity bills via peak shaving & time-of-use
- Grid feed-in for utility credits
- AC Coupling retrofitting existing grid-tie systems

- Support battery heterogeneity across different types or same-type with varying capacities
- Scalable up to 3 units in parallel
- Built-in 3 MPPT trackers for flexible system design and higher yields
- Built-in EMS with 8 time periods for battery charging & discharging
- 0-10ms UPS ability
- Intelligent control

Easy O&M

- Support CAN, RS485, and DRM
- Local monitoring via E4 LCD Monitor
- Remote monitoring and control via Nova Web & APP

Model No.	Ingesola 10T	Ingesola 12T	Ingesola15T	
Grid input		\/		
Grid feedback	TI 1 00	Yes		
Nominal AC input voltage		Three phase 3P4W+PE, 220/380Vac, 230/400Vac, 240/415Vac, 50/60Hz		
AC Input range	-25%~+20% or Accord	-25%~+20% or According to Grid Code Standard; 50Hz:+/-5Hz; 60Hz:+/-5Hz		
AC input Current (transfer switch)		45A		
AC Input Current Limit Function & Surge Protection		Yes		
Generator input				
Nominal AC input voltage	Three phase 3P4W+PE, 220/380Vac, 230/400Vac, 240/415Vac, 50/60Hz			
AC Input range		-25%~+20%; 40Hz-70Hz		
AC input Current (transfer switch)	32A			
AC Input Current Limit Function		Yes		
Inverter				
Nominal AC output range	· ·	3P4W+PE, 230/400Vac+/-2%; 50/		
Harmonic distortion		ear load<2%,Non-linear load <		
Nominal Output Power	10000VA	12000VA	15000VA	
Max. AC output power	11000VA	13200VA	16500VA	
Peak power (off grid)	20000VA 60S	24000VA 60S	30000VA 10S	
Nominal AC Output Current	15.2A	18.2A	22A	
Maximum efficiency	97.8%	97.8%	97.8%	
Zero load power (W)	80	80	80	
DC				
DC Voltage Range		40V-60V		
Battery types	L	ead acid battery, Lithium battery	У	
Charging strategy for Li-Ion battery		Self adaption to BMS		
Max. Charging/ Discharging Current	210A/210A	250A/250A	300A/300A	
Solar				
Max. DC input power	10500W			
Max. PV Input Voltage		19500W		
Max. PV Input Voltage MPPT Voltage Range / Start-up Voltage		1000V 150-800V / 160V		
Max. PV Input Current / Max.Short Current		150-800V / 160V 16A+16A+16A / 20A+20A+20A		
MPPT Number / No. Strings Per MPPT Tracker		3/1+1+1		
PIFF I NUMBE / NO. SUNGS PERMPT TRACKER		3/		
General				
Backup	UPS			
Max. AC Pass-through Current	32A			
Protection	a) output short circuit, b) overload, c) battery voltage too high, d) battery voltage too low, e) temperature too high, f) input voltage out of range, g) input voltage ripple too high, h) Fan block			
CAN Bus communication port	For parallel operation			
	DRM, RS485			
General purpose com. Port	LED+ External Touch LCD screen			
· · ·	I I	LED+ External Touch LCD screen		
Display		LED+ External Touch LCD screen >45°C de-rating; 95% without co		
Display Operating temperature range & relative humidity				
Display Operating temperature range & relative humidity Altitude (m)		>45°C de-rating; 95% without co		
Display Operating temperature range & relative humidity Altitude (m) Dimension (Wx D x H) (mm)		>45°C de-rating; 95% without co 3000		
Display Operating temperature range & relative humidity Altitude (m) Dimension (Wx D x H) (mm) Weight (kg)	-25°C~60°C	>45°C de-rating; 95% without co 3000 484*250*740	ndensation	
Display Operating temperature range & relative humidity Altitude (m) Dimension (Wx D x H) (mm) Weight (kg) IP Protection	-25°C~60°C	>45°C de-rating; 95% without co 3000 484*250*740 31	ndensation 32	
General purpose com. Port Display Operating temperature range & relative humidity Altitude (m) Dimension (Wx D x H) (mm) Weight (kg) IP Protection Grid Regulation Safety & EMC	-25°C~60°C 30 AS/NZS 4777.2	>45°C de-rating; 95% without co 3000 484*250*740 31 IP65 (Outdoor)	32 3, NRS097-2-1	

ESS Applications

Ingesola is designed for low voltage batteries



Work with Solar

Hybrid ESS Solution


Optimize self-consumption by allocating surplus solar energy to power loads at the AC inputs, reducing system initial investment.



The following two solutions are suitable for scenarios with more energy consumption in the day and less consumption at night, like offices.


Hybrid ESS Solution with AC Coupled PV on Input

Mostly for retrofitting an existing PV grid-tie system into an ESS system by adding a CT or Energy Meter.



Hybrid ESS Solution with AC Coupled PV on Output

Mostly for retrofitting an existing PV grid-tie system into an AC Coupled PV ESS system without adding CT or Energy Meter. When the grid fails in the daytime, the PV inverter can also keep generating electricity.



Power Backup Solution

Suitable for a newly installed system. Application scenario: unstable grid or non-stop power supply required, like fire fighting systems.




(\Rightarrow)

Work with EV Charger & V2G Charger


Pair Energy Storage System with EV Chargers

The EVs can be charged with surplus solar energy, with the battery if the battery SoC is higher than a certain level, or with grid power during low or negative price periods, to realize time-of-use arbitrage and cut your bills.



Pair Energy Storage System with V2G Chargers

When working with the V2G chargers, the system can charge the EVs with surplus solar to save bills. When the PV and the battery are not enough to power loads, the system can also draw the stored energy from EVs to compensate the insufficient part.



TBB NOVA APP & Web

Monitor and Control Your Solar System Anywhere Anytime

NOVA App and NOVA Web are FREE energy management and monitoring system designed by TBB Renewable, displaying real-time data of all system components and history records, providing easy access to controlling the power generation and power consumption. According to historical data, users can actively adjust and optimize power consumption habits.



Comprehensive Monitoring

- Live data and status overview and system analysis
- System configuration and parameter setting
- Customizable alarm setting
- Detailed report for power harvest, storage and consumption in visual chart and graph
- WEB compatible for Windows and Mac PC
- APP available for Android and iOS phone

Intelligent Management for Dealers / Installers

- Comprehensive management for multiple installations
- Catch potential issues early with alarm setting to prevent system failure
- Optimize the energy harvest and usage with history graphs and detailed analytical reports
- Proactive maintenance services to keep good relationship with customers
- Customizable banner to show dealers information and slogan





nova.tbbrenewable.com








Residential Hybrid ESS Solution

T B B R E N E W A B L E



- Hybrid Inverter -



TBB Ingesola P8/P10/P12 series are split-phase hybrid inverters for residential hybrid ESS, to cut electricity cost and reliance on the grid. Suitable for low voltage battery (48V) systems, it features 3 MPPT trackers, and supports both off-grid and grid-tie operations.

It offers a smart port for configurations like secondary AC output, AC Coupling for retrofitting, generator input for backup power, and EV charging with EV and V2G chargers. Ideal for optimizing self-consumption, the Ingesola series also includes an EMS for peak shaving with eight configurable time periods for charging and discharging, and has an IP65-rated design for durability in harsh environments.

Enhanced Flexibility

- Supports both off-grid and grid-tie operations
- For Hybrid ESS, AC Coupling Retrofitting, Backup Power and EV Charging applications
- Two AC inputs or two AC outputs
- Smart port for GEN input, AC Coupling with PV inverter, EV charging, or 2nd AC output

Superior Reliability

- Max. charging/discharging current of 210A
- Dust-and water-proof IP65 rated enclosure

ESS Capabilities

- Maximize self-consumption
- Lower electricity bills via peak shaving & time-of-use
- Grid feed-in for utility credits
- AC Coupling retrofitting existing grid-tie systems

- Support battery heterogeneity across different types or same-type with varying capacities
- Scalable up to 3 units in parallel
- Built-in 3 MPPT trackers for flexible system design and higher yields
- Built-in EMS with 8 time periods for battery charging & discharging
- 0-10ms UPS ability
- Intelligent control

Easy O&M

- Support CAN and RS485
- Local monitoring via E4 LCD Monitor
- Remote monitoring and control via Nova Web & APP

Model No.	Ingesola P8	Ingesola P10	Ingesola P12
Grid input			
Grid feedback		Yes	
Nominal AC input voltage (VAC)	Yes Split phase 120/240, 2/3 phase 208		
AC Input Voltage Range (VAC)	-25%~+15%,Split phase : 180~280@240 (L1-L2); 90-138@120V (L1/2-N) 2/3 phase: L1-L2 156~240@208 (L1-L2); 90-138@120V (L1/2-N)		
AC Input Frequency Range (Hz)	, , , , , , , , , , , , , , , , , , ,	50: +/-5; 60: +/-5	
AC Input Current (transfer switch) (A)	200	200	200
AC Input Current Limit Function & Surge Protection		Yes	
, , , , , , , , , , , , , , , , , , ,			
Generator input			
Nominal AC Input Voltage (VAC)	Spl	it phase 120/240 ; 2/3 phase 2	08
AC Input Range (VAC)	-25%~+15%, Split phase : 180~280@240 (L1-L2); 90-138@120V (L1/2-N)2/3 phase: L1-L2 156~240@208 (L1-L2); 90-138@120V (L1/2-N)		
AC Input Frequency Range (Hz)		40-70	
AC Input Current (transfer switch) (A)	200	200	200
AC Input Current Limit Function		Yes	
Inverter			
Nominal AC output voltage (VAC)	Spl	it phase 120/240, 2/3 phase 20	08
Nominal AC output frequency (Hz)	50/60 +/-0.1%		
Harmonic distortion	Linear load<2%, Non-linear load <5%		
Nominal Output Power (VA)*	8000	10000	12000
Max. AC output power (VA)	8800	11000	13200
Peak power (off grid)		2 Times of Rated Power, 10s	
Nominal / Max. AC Output Current (A)	25 / 37.5	33.3 / 50	41.6 / 50
DC			
DC Voltage Range (V)	40-60	40-60	40-60
Battery types	Lead acid battery, Lithium battery		
Charging strategy for Li-Ion battery	Self adaption to BMS		
Max. Charging/ Discharging Current (A)	125/125	167/167	210/210
Calan			
Solar May DC input payor (W)	0000	12000	15000
Max. DC input power (W)	9000	12000	15000
Max. PV Input Voltage (V) MPPT Voltage Range /Start-up Voltage (V)	500		
MPPT voltage Range /Start-up voltage (V) Max. PV Input Current / Max.Short Current (A)	125-430 / 160		22+22+22
Max. PV Input Current / Max.Snort Current (A) MPPT Number / No. Strings Per MPPT Tracker	20+20 / 22+22 2 / 1+1 2 / 1+1 3 / 1+1+1		
min i rivalitoet / tvo. Suttigs Fet PIFFT Hacket	Z / 1 · 1	371	- 1 - 1
General			
General Backup	UPS	UPS	UPS
Max.AC Pass-through Current (A)	200	200	200
Protection	a) output short circuit; b) overload, c) battery voltage too high, d) battery voltage too low, e) temperature too high, f) input voltage out of range, g) input voltage ripple too high, h) Fan block		
CAN Bus communication port		For parallel operation	
General purpose com. Port		RS485, CAN (BMS)	
Display		LED	
Operating temperature range & relative humidity	-25°C~60°C>45°Cde-rating; 95% without condensation		
Altitude (m)		3000	
IP Protection		IP65 (Outdoor)	
Grid Regulation	IEEE 1547, IEEE 1547.1, U	JL 1741SA, CA Rule 21, Hawaii	an Rule14H, PRC-024-1
Safety & EMC	UL 174	11, CSA C22.2 No. 107.1, FCC P	art 15
Warranty	5 Voor Produc	ct Warranty, 10 Year Performan	oce Warranty

^{*} When PV energy is sufficient

ESS Applications

Ingesola is designed for low voltage batteries



Work with Solar

Hybrid ESS Solution


Optimize self-consumption by allocating surplus solar energy to power loads at the AC inputs, reducing system initial investment.



The following two solutions are suitable for scenarios with more energy consumption in the day and less consumption at night, like offices.


Hybrid ESS Solution with AC Coupled PV on Input

Mostly for retrofitting an existing PV grid-tie system into an ESS system by adding a CT or Energy Meter.



Hybrid ESS Solution with AC Coupled PV on Output

Mostly for retrofitting an existing PV grid-tie system into an AC Coupled PV ESS system without adding CT or Energy Meter. When the grid fails in the daytime, the PV inverter can also keep generating electricity.



Power Backup Solution

Suitable for a newly installed system. Application scenario: unstable grid or non-stop power supply required, like fire fighting systems.




(\Rightarrow)

Work with EV Charger & V2G Charger


Pair Energy Storage System with EV Chargers

The EVs can be charged with surplus solar energy, with the battery if the battery SoC is higher than a certain level, or with grid power during low or negative price periods, to realize time-of-use arbitrage and cut your bills.



Pair Energy Storage System with V2G Chargers

When working with the V2G chargers, the system can charge the EVs with surplus solar to save bills. When the PV and the battery are not enough to power loads, the system can also draw the stored energy from EVs to compensate the insufficient part.



TBB NOVA APP & Web

Monitor and Control Your Solar System Anywhere Anytime

NOVA App and NOVA Web are FREE energy management and monitoring system designed by TBB Renewable, displaying real-time data of all system components and history records, providing easy access to controlling the power generation and power consumption. According to historical data, users can actively adjust and optimize power consumption habits.



Comprehensive Monitoring

- Live data and status overview and system analysis
- System configuration and parameter setting
- Customizable alarm setting
- Detailed report for power harvest, storage and consumption in visual chart and graph
- WEB compatible for Windows and Mac PC
- APP available for Android and iOS phone

Intelligent Management for Dealers / Installers

- Comprehensive management for multiple installations
- Catch potential issues early with alarm setting to prevent system failure
- Optimize the energy harvest and usage with history graphs and detailed analytical reports
- Proactive maintenance services to keep good relationship with customers
- Customizable banner to show dealers information and slogan





nova.tbbrenewable.com








Residential Hybrid ESS Solution

T B B R E N E W A B L E



- Hybrid Inverter -



TBB Ingesola S5/S8 series are single-phase hybrid inverters for residential hybrid ESS, to cut electricity cost and reliance on the grid. Suitable for low voltage battery (48V) systems, it features a 1.5 max DC/AC ratio and 2 MPPT trackers for efficient solar integration. It supports both off-grid and grid-tie operations.

It offers a smart port for configurations like secondary AC output, AC Coupling for retrofitting, generator input for backup power, and EV charging with EV and V2G chargers. Ideal for optimizing self-consumption, the Ingesola series also includes an EMS for peak shaving with eight configurable time periods for charging and discharging, and has an IP65-rated design for durability in harsh environments.

Enhanced Flexibility

- Supports both off-grid and grid-tie operations
- For Hybrid ESS, AC Coupling Retrofitting, Backup Power and EV Charging applications
- Two AC inputs or two AC outputs
- Smart port for GEN input, AC Coupling with PV inverter, EV charging, or 2nd AC output

Superior Reliability

- Max. charging/discharging current of 190A
- Dust-and water-proof IP65 rated enclosure

ESS Capabilities

- Maximize self-consumption
- Lower electricity bills via peak shaving & time-of-use
- Grid feed-in for utility credits
- AC Coupling retrofitting existing grid-tie systems

- Support battery heterogeneity across different types or same-type with varying capacities
- Parallel and three-phase up to 9 units
- Built-in 2 MPPT trackers for flexible system design and higher yields
- Built-in EMS with 8 time periods for battery charging & discharging
- 0-10ms UPS ability
- Intelligent control

Easy O&M

- Support CAN, RS485, and DRM
- Local monitoring via E4 LCD Monitor
- Remote monitoring and control via Nova Web & APP

Model No.	Ingesola S5	Ingesola S8	
Crid input			
Grid input		,	
Grid feedback	Yes		
Nominal AC input voltage		230/240Vac, 50/60Hz	
AC Input range	-20%~+20% or According Grid Code Standard; 50Hz:+/-5Hz; 60Hz:+/-5Hz		
AC input Current (transfer switch)		0A ,	
AC Input Current Limit Function & Surge Protection	Y	⁄es	
Generator input			
Nominal AC input voltage	Single phase, 220/230/240Vac, 50/60Hz		
AC Input range	-20%~+20%	5; 40Hz-70Hz	
AC input Current (transfer switch)	5	0A	
AC Input Current Limit Function	Y	/es	
las sa uthors			
Inverter	0: 1 1 277	. / . 20% . 50 / / 01 / . 0.40%	
Nominal AC output range		+/-2%; 50/60Hz+/-0.1%	
Harmonic distortion		Non-linear load <5%	
Nominal Output Power	5000VA	8000VA	
Max. AC output power	5500VA	8800VA	
Peak power (off grid)	10000VA 10S	16000VA 10S	
Nominal AC Output Current	22.7A	36.4A	
Maximum efficiency	97.8%	97.8%	
Zero load power (W)	40W	45W	
DC			
DC Voltage Range	42V-60V		
Battery types	Lead acid battery, Lithium battery (Self adaption to BMS)		
Max. Charging/ Discharging Current	120A/120A	190A/190A	
Calan			
Solar	750014	1000011	
Max. DC input power	7500W	12000W	
Max. PV Input Voltage	500V		
MPPT Voltage Range / Start-up Voltage	120-425V / 160V		
Max. PV Input Current / Max.Short Current	25A+25A / 25A+25A		
MPPT Number / No. Strings Per MPPT Tracker	27	1+1	
General			
Backup	U	JPS .	
Max. AC Pass-through Current	50A		
Protection	a) output short circuit, b) overload , c) battery voltage too high , d) battery voltage too low, e) temperature too high, f) input voltage out of range, g) input voltage ripple too high, h) Fan block		
CAN Bus communication port	For parallel and three phase operation		
General purpose com. Port	DRM, RS485		
Display	LED+ External Touch LCD screen		
Operating temperature range & relative humidity	-40°C~65°C, >45°C de-rating; 95% without condensation		
- · · · · · · · · · · · · · · · · · · ·	4000		
Altitude (m)	IP65 (Outdoor)		
IP Protection	IP65 (C		
Altitude (m) IP Protection Grid Regulation Safety & EMC	IP65 (C	Outdoor) 6, IEC60068, IEC61683, NRS097-2-1	

ESS Applications

Ingesola is designed for low voltage batteries



Work with Solar

Hybrid ESS Solution


Optimize self-consumption by allocating surplus solar energy to power loads at the AC inputs, reducing system initial investment.



The following two solutions are suitable for scenarios with more energy consumption in the day and less consumption at night, like offices.


Hybrid ESS Solution with AC Coupled PV on Input

Mostly for retrofitting an existing PV grid-tie system into an ESS system by adding a CT or Energy Meter.



Hybrid ESS Solution with AC Coupled PV on Output

Mostly for retrofitting an existing PV grid-tie system into an AC Coupled PV ESS system without adding CT or Energy Meter. When the grid fails in the daytime, the PV inverter can also keep generating electricity.



Power Backup Solution

Suitable for a newly installed system. Application scenario: unstable grid or non-stop power supply required, like fire fighting systems.




(\Rightarrow)

Work with EV Charger & V2G Charger


Pair Energy Storage System with EV Chargers

The EVs can be charged with surplus solar energy, with the battery if the battery SoC is higher than a certain level, or with grid power during low or negative price periods, to realize time-of-use arbitrage and cut your bills.



Pair Energy Storage System with V2G Chargers

When working with the V2G chargers, the system can charge the EVs with surplus solar to save bills. When the PV and the battery are not enough to power loads, the system can also draw the stored energy from EVs to compensate the insufficient part.



TBB NOVA APP & Web

Monitor and Control Your Solar System Anywhere Anytime

NOVA App and NOVA Web are FREE energy management and monitoring system designed by TBB Renewable, displaying real-time data of all system components and history records, providing easy access to controlling the power generation and power consumption. According to historical data, users can actively adjust and optimize power consumption habits.



Comprehensive Monitoring

- Live data and status overview and system analysis
- System configuration and parameter setting
- Customizable alarm setting
- Detailed report for power harvest, storage and consumption in visual chart and graph
- WEB compatible for Windows and Mac PC
- APP available for Android and iOS phone

Intelligent Management for Dealers / Installers

- Comprehensive management for multiple installations
- Catch potential issues early with alarm setting to prevent system failure
- Optimize the energy harvest and usage with history graphs and detailed analytical reports
- Proactive maintenance services to keep good relationship with customers
- Customizable banner to show dealers information and slogan





nova.tbbrenewable.com







Residential Hybrid ESS Solution

T B B R E N E W A B L E