

# SH15/20/25T

Hybrid Three Phase Inverter



## FULL BACKUP

- Built-in 63 A bypass for whole home backup
- 10 ms seamless switch
- Peak output up to 36500 VA ( 10 s ) in backup mode ( SH25T )



## FLEXIBLE APPLICATION

- Support 100 % unbalance output in backup and on grid mode
- Max. 16 A DC input current per string
- 50 A fast charge / discharge current



## FRIENDLY INSTALLATION

- Plug & Play installation
- Quiet operation for indoor or outdoor installation



## SAFE AND DURABLE

- Support precise AFCI
- IP65/C5



Type designation	SH15T	SH20T	SH25T
<b>Input (DC)</b>			
Max. PV input power	30000 Wp	40000 Wp	50000 Wp
Max. PV input voltage *		1000 V	
Min. PV input voltage / Startup input voltage		150 V / 180 V	
Rated PV input voltage		600 V	
MPPT operating voltage range **		150 V - 950 V	
No. of independent MPP trackers		3	
No. of PV strings per MPPT		2 / 2 / 1	
Max. PV input current		80 A ( 32 A / 32 A / 16 A )	
Max. DC short-circuit current		100 A ( 40 A / 40 A / 20 A )	
Max. current for input connector		30 A	
<b>Battery data</b>			
Battery type		Li-ion battery	
Battery voltage range		100 V - 700 V	
Max. charge / discharge current ***		50 A / 50 A	
Max. charge / discharge power	30000 W / 15000 W	30000 W / 20000 W	30000 W / 25000 W
<b>Input and Output (AC)</b>			
Max. AC power from grid ****		43000 VA	
Rated AC output power	15000 W	20000 W	25000 W
Max. AC output apparent power	15000 VA	20000 VA	25000 VA
Max. AC output current	22.8 A	30.4 A	37.9 A
Rated AC voltage		3 / N / PE, 220 V / 380 V ; 230 V / 400 V; 240 V / 415 V	
AC voltage range		270 V - 480 V	
Rated grid frequency		50 Hz / 60 Hz	
Grid frequency range		45 Hz - 55 Hz / 55 Hz - 65 Hz	
Harmonic (THD)		< 3 % (of rated power)	
Power factor at rated power / Adjustable power factor		> 0.99 / 0.8 leading to 0.8 lagging	
Feed-in phases/connection phases		3 / 3-N-PE	
<b>Backup data (on grid mode)</b>			
Max. output power for backup load ****		43000 W	
Max. output current for backup load		3 * 63 A	
<b>Backup data (off-grid mode)</b>			
Rated voltage		3 / N / PE, 220 / 380 V; 230 / 400 V; 240 / 415 V ( ± 2 %)	
Rated frequency		50 Hz / 60 Hz ( ± 0.2 % )	
THDV(@Linear load)		< 2 %	
Backup switch time		< 10 ms	
Rated output power	15000 W / 15000 VA	20000 W / 20000 VA	25000 W / 25000 VA
Peak output power *****	25500 W / 25500 VA , 10 s	32000 W / 32000 VA , 10s	36500 W / 36500 VA , 10 s
<b>Efficiency</b>			
Max. efficiency / European efficiency	98.1 % / 97.6 %		98.2 % / 97.8 %
<b>Protection &amp; Function</b>			
Grid monitoring		Yes	
DC reverse polarity protection		Yes	
AC short-circuit protection		Yes	
Leakage current protection		Yes	
DC switch (solar)		Yes	
Surge protection		DC Type II / AC Type II	
PID zero		Yes	
Battery input reverse polarity protection		Yes	
<b>General data</b>			
Topology (solar / battery)		Transformerless / Transformerless	
Degree of protection		IP65	
Protective class		Protective class I	
Overvoltage category		III[AC]; II[PV]; [BATTERY]	
Active anti-islanding method		Frequency shift	
Dimensions (W * H * D)		620 mm * 480 mm * 245 mm	
Weight	38 kg		40 kg
Mounting method		Wall-mounting bracket	
Operating ambient temperature range		-25 °C - 60 °C	
Allowable relative humidity range(Non-condensing)		0 % - 100 %	
Cooling method	Natural convection		Fan cooling
Max. operating altitude		2000 m	
Noise(Typical)	35 dB ( A )		50 dB ( A )
Display		LED	
Communication		RS485, WLAN, Ethernet, CAN	
DI / DO		DI * 4 / DO * 2 / DRMO	
DC connection type	Plug and play connector ( PV, Max.6mm <sup>2</sup> / battery, Max.10mm <sup>2</sup> )		
AC connection type	Plug and play connector ( Max.16 mm <sup>2</sup> )		
Compliance	IEC / EN 62109, IEC 61000-6, EN 62477-1, IEC 61727, IEC 62116, IEC 62920, EN 55011, CISPR 11, VDE-AR-N-4105, EN 50549-1, NRS 097, AS/NZS 4777.2:2020, TOR Type A, R25, CEI 0-21		
Country of manufacture	China		

\* Input voltage exceeding the MPPT operating voltage range triggers inverter protection \*\* Please refer to the user manual for the full load MPPT voltage range \*\*\* Depending on the connected battery \*\*\*\* Please refer to the user manual and modify the settings based on actual load power \*\*\*\*\* Can be reached only if PV and battery power is sufficient

