

INVERTER SMILE5-INV



Technical Specification

PV Input (DC)

Maximum Input PV Power	2 x 3300 W
Maximum DC Voltage	580 V
Nominal DC Voltage	360 V
Start-up DC Voltage	125 V
MPPT Voltage Range	125 ~ 550 V
MPPT Number	2
Maximum Input Current	2 x 12 A
Maximum Short-circuit Current	2 x 15 A

Grid Output (AC)

Rated Power	4600 W
UPS(Resistive load)	Yes
Nominal Output Voltage	230 V
Output Voltage Range	180 ~ 270 V
Maximum Output Current	22 A
Output Power Factor	0.8 leading to 0.8 lagging
Grid Connection	Single-phase

Battery Input (DC)

Nominal DC Voltage	48 V
DC Voltage Range	40 ~ 60 V
Maximum Charging Current	100 A
Maximum Discharging Power	4600 W
Compatible Chemistry	LFP

Efficiency

Maximum Efficiency	97.6%
EURO Efficiency	97.0%

Headquarter: Alpha ESS Co., Ltd.

☎ +86 513 8060 6891
✉ info@alpha-ess.com
🌐 www.alpha-ess.com
📍 Jiuhua Road 888, Nantong High-Tech Industrial Development Zone, Nantong City, 226300

Alpha ESS Suzhou Co., Ltd.

☎ +86 512 6828 7609
✉ info@alpha-ess.com
🌐 www.alpha-ess.com
📍 Building 10-A, Canal Town Industrial Park, 99 Taihu E Rd, Wuzhong District, Suzhou 215000

Australia: Alpha ESS Australia Pty. Ltd.

☎ +61 402 500 520 (Sales)
+61 1300 968 933 (Technical Support)
✉ australia@alpha-ess.com
🌐 www.alpha-ess.com.au
📍 Suite 1, Level 1, 530 Botany Road, Alexandria, NSW, 2015

Germany: Alpha ESS Europe GmbH

☎ +49 6103 4591 601
✉ europe@alpha-ess.de
🌐 www.alpha-ess.de
📍 Paul-Ehrlich-Straße 1a, D-63225 Langen, Hessen

Italy: Alpha ESS Italy S.r.l.

☎ +39 599 239 50
✉ info@alpha-ess.it
🌐 www.alpha-ess.it
📍 Via Loda, 17-41013 Castelfranco Emilia (MO)

Korea: Alpha ESS Korea Co., Ltd.

☎ +82 64 721 2004
✉ korea@alpha-ess.com
📍 2F, 19-4, Nohyeong 11-gil, Jeju-si, Jeju-do, Republic of Korea

UK: Alpha ESS UK Ltd.

✉ uk@alpha-ess.com
📍 Drake House, Long Street, Dursley, gl11 4hh